

MAG1000



USER MANUAL

Magnetotherapy model NEW MAG1000

MAG1000

SUMMARY	XXVII
TECHNICAL SPECIFICATIONS	28
MANUFACTURER	28
DECLARATION OF CONFORMITY	28
CLASSIFICATIONS.....	28
PURPOSE AND SCOPE	29
TECHINICAL FEATURES.....	30
DEVICE AND COMMANDS DESCRIPTION.....	31
LABELLING	32
<i>Package content</i>	34
HOW TO USE.....	35
INTRODUCTION TO TECHNOLOGY.....	35
CONTRINDICATIONS.....	36
<i>Side effects</i>	36
WARNINGS.....	36
PATIENT PREPARATION: POSITIONING OF THE THERAPEUTIC BELT	37
INSTRUCTIONS FOR USE	38
DEVICE CARE	41
MAINTENANCE	41
TROUBLESHOOTING	42
<i>Battery charging</i>	42
<i>Replacing the battery</i>	42
DISPOSAL	43
WARRANTY	44
<i>Assistance</i>	45
<i>Spare parts</i>	45
INTERFERENCE AND ELCTROMAGNETIC COMPATIBILITY TABLES	45

Manufacturer**Shenzhen Dongdixin Technology Co., Ltd.**

Floor 1-2, No.3 Building, Fanshen Xusheng Industrial Estate

Xilixiaobaimang 518108 Nanshan District, Shenzhen P.R. China

(CE certificate n° HD 60147882 0001 issued by TÜV Rheinland LGA Products GmbH notified body n°0197).

Authorised representative**Shanghai International Holding Corp. GmbH (Europe)**

Eiffestraße 80, 20537 Hamburg, Germany

Importer**I.A.C.E.R. S.r.l.**

Via Enzo Ferrari 2 • 30037 Scorzè (VE)

Tel. 041.5401356 • Fax 041.5402684

Declaration of conformity**Shenzhen Dongdixin Technology Co., Ltd**

Floor 1-2, No.3 Building, Fanshen Xusheng Industrial Estate

Xilixiaobaimang 518108 Nanshan District, Shenzhen P.R. China

herewith declares under its own responsibility, that the product

Model: NEW MAG1000**Name: MAG1000**

has been designed and manufactured according to the European Medical Device Directive 93/42/EEC (transposed in Italy by the D.Lgs. 46/97), as modified by the Directive 2007/47/EC (D.Lgs.37/2010) and further modifications/integrations.

The products have been assigned to class IIa, according to Annex IX, rule 9 of the Directive 93/42/EEC (and further modifications/integrations) and bear the mark



Compliance of the concerned products with the Directive 93/42/EEC has been assessed and certified by the notified body:

0197 – TÜV Rheinland LGA Products GmbH

Tillystraße 2 – 90431 Nürnberg, Germany

Certificate n°: HD 60147882 0001

following the certification procedure according to Annex II (excluding point 4) of the Directive 93/42/EEC.

Classifications

From now on, for the sake of simplicity, in this user manual, reference will be made to the device MAG1000 meaning the device model NEW MAG1000, name MAG1000.

MAG1000 has the following specifications:

- class IIa equipment (Directive 93/42/CEE, Annexed IX, rule 9 and following modifications).
- Class II applied part type BF (classif. EN 60601-1).
- Equipment not protected against liquids penetration.
- Equipment and accessories not subjected to sterilization;
- Use of the equipment is prohibited close to flammable substances or in environments with high concentrations of oxygen;
- Continuous operating mode equipment;
- Equipment not suited to be used in external.

Purpose and scope

Clinical Purpose: Therapeutic

Scope of Use: Ambulatory and domestic

MAG1000 is projected and indicated for healing, rehabilitation and functional recovery treatments for pathologies of:

- wrist articulation
- hand articulation
- shoulder articulation
- foot articulation
- ankle articulation
- knee articulation
- skeletal motor apparatus

- arthrosis
- atrophies and muscular distrofie
- bursitis
- bruises
- degeneration of locomotor apparatus
- sprains
- periarthrititis
- benign lesions and muscular tears
- tendonitis

MAG1000 is particularly suitable for the treatment and the care of the osteoporosis and all the pathologies on bony tissue.

MAG1000 is a device intended for both the professional user (physician, therapist, etc.) and the patient at home. **In case of home therapy, the use of the device is recommended only on indication of the physician/therapist.**

The patient population intended for magnetotherapy treatment using the MAG1000 device includes patients of both sexes, men and women, of age (unless otherwise indicated by medical doctors). For further details, please refer to the *Contraindications* section.

Technical features

Characteristics	Specification	
Power supply	Rechargeable batteries, Ni-MH AA2300mAh 4,8V	
Battery charger	Input AC 110-240V, 50/60Hz, 200mA; Output DC 6.8V, 300mA	
Max current absorbed	≤150mA (therapy mode)	
Isolation class (EN 60601-1)	II	
Applied part (EN 60601-1)	BF	
Field intensity	40mW for channel Adjustable on 3 levels: low, medium, high	
Carrier frequency	27MHz	
Squared wave frequency	From 8 to 640Hz	
Number of programmes	20	
Dimensions (length x width x height))	153x91x38mm	
Environmental conditions of	Temperature	From +5° to +40°C

Characteristics	Specification	
operation	Relative humidity	From 30% to 80%
	Pressure	From 500 to 1060hPa
Transport and storage conditions	Temperature	From -10° to +55°C
	Relative humidity	From 10% to 90%
	Pressure	From 500 to 1060hPa

Expected lifetime: 3 years.

Device and commands description



ON/OFF Key



Start/pause key

TM.

Time set key

PR.

Programs selection key

IN.

Field intensity key



Battery status indication

PROGRAM P-01

Selected program for therapy

PULSE RATE 8Hz

Selected pulse rate

INTENSITY

Magnetic field intensity level selected:

1 - low, **2** - medium, **3** - high


TIMER 45'00"

Therapy time (minutes and seconds)














A/B



Working channel: **A** - channel1, **B** - channel2

Labelling



The label on the side is placed on the back of the device

Symbol	Description
	Importer logo
	Certification of the product issued by the notified body N° 0197.
	Manufacturer
	Authorised representative.
	Importer.
	Manufacturing date
	Attention, consult operating instructions.
	Product subject to WEEE regulations concerning separate waste collection of electronic equipment.
	Class II equipment.
	Applied part type BF.
	Permitted storage temperatures (on the box)
	Relative humidity of storage (on the box)
	Atmospheric pressure (atmospheric pressure for transport and storage, packaging)
IP22	Medical device protected against the penetration of solids (with a diameter $d \geq 12,5\text{mm}$) and against the vertical drops when the device is kept at 15° from its normal functioning position.

Symbol	Description
	Power supply (DC 6.8V / 0.3A).
A B	A / B (CH1 / CH2) channel 1/2.
	Non ionizing

Package content

The Mag1000 package contains:

- n°1 MAG1000 device;
- n°1 elastic therapeutic belt;
- n°1 battery pack (inside the device);
- n°1 battery charger;
- n°1 user manual;
- n°1 carrying bag.

Introduction to technology

Electromagnetotherapy distinguishes itself from the “traditional” magnetotherapy since it uses high frequency electromagnets instead of permanent magnets: particularly, we refer to electromagnetotherapy when using devices emitting high frequency and low intensity pulsed electromagnetic fields (PEMF, carrying frequency from 20 to 30 MHz, with frequencies up to 5.000 Hz).

The MAG1000 has been designed to exploit these fields, in fact it generates an electric signal with a carrier frequency of 27mhz, which is modulated with specific frequencies and therefore is able to soothe the anatomical site affected by pain. For this purpose, electromagnetic fields are generated by a radiant circuit (antennas) contained inside a special ergonomic container and therefore exploited mainly in the treatments for pain, that is to restore the biomagnetic cell field that with the disease had weakened. In fact, PEMFs are able to return to the altered biological system the ability to react with more energy against the damaging process, giving back to the cells the optimal energy lost.

The use of high frequency and to low intensity PEMFs, allows to get ample therapeutic results without collateral effects. This also allows the use in acute pathological trials. The electromagnetotherapy is particularly suitable for the care of the soft tissues pathologies, with extraordinary results in the regeneration of the tissues themselves.

Due to its characteristics, the electromagnetotherapy is universally recognized as the most suitable technique for the treatment of the bony pathologies, in particular for the osteoporosis.

There are lots of effects that can be brought back to electromagnetotherapy: the piezoelectric effect, the effect of orientation of the collagen, the stimulation of the calcic deposition (*Barker - Lunt 1983, Bassett – Pawluk – Pilla 1974, Bassett - Valdes – Hernandez 1982*).

Since the present day, all the equipments of electromagnetotherapy were built particularly to satisfy or the medical sector (with high prices) or the economic demands of patients, but with products of low quality.

MAG1000 is born really to reconcile the demand to have an equivalent device, for performances and effectiveness, to those devoted to medical sector, also maintaining a simplicity of use and an extremely favorable price.

Contraindications

Patient in pregnancy, tuberculosis, juvenile diabetes, viral (in acute phase) illnesses, mycosis, cardiopathic subjects, serious arrhythmias or pacemaker carriers, children, metallic prosthesis carriers, acute infections, epileptics (**different medical prescriptions excepted**).

The functioning of some electric implantable devices, such as pacemakers, could be compromised during a treatment with a short-wave therapy device. Consult a physician before starting the treatment.

Side effects

No significant side effects are known of, nor are reported particular contraindications for excessive time length using the device.

Warnings

It is recommended to:

- check the position and the meaning of all the labels on the equipment;
- do not damage the applicator by acting on the connecting wire, and do not wrap the wire around the applicator or the appliance;
- check the integrity of the power supply before each use. Avoid use in case of signs of damage to the casing or to the connecting wire;
- avoid the use of the system to persons not adequately educated by reading the manual;
- ONLY use cables and applicators supplied by the manufacturer. Inadequate cables and applicators may damage the appliance and/or damage the patient;
- during therapy it is advisable to the patient and user not to wear metallic objects.

Is prohibited:

- the use of the device by persons incapable of understanding and wanting, suffering from sensitiveness to sensitivity, temporarily incapacitated if not assisted by qualified personnel;
- the use of the device near inflammable substances, gases, explosives, in environments with high concentrations of oxygen, in the presence of aerosols or in very humid environments (do not use in the bathroom or during the shower/bath);
- the use of the appliance in the presence of signs of deterioration and/or damage to the same or to the accessories (electrodes, chargers, etc.) and/or cables; contact the dealer or IACER Srl in accordance with the *Assistance* section. Check the integrity before each use;

- the use of the appliance contemporary to liniments containing free ions of magnetic metals;
- to connect the device and its accessories to other devices not listed in this manual.

Warning:

- to connect the device and its accessories to other devices not listed in this manual;
- to connect the device and its accessories to other devices not listed in this manual;
- the use of the connection cables of the belt and the feeder: danger of strangulation. Be extremely careful if it is necessary to pass the cables near the neck and the patient's head: In this case it is necessary to maintain a safe position and to avoid abrupt movements that can cause the cables to twist;
- to avoid exposing the device and its accessories to excessive direct light and dust. See the paragraph *Care of the device*.



WARNING! Connect the battery charger plug to 230V main only when connected to MAG1000 device for batteries recharging. Disconnect the battery charger from main after each use.



WARNING! During therapy it is possible to hear a light hiss coming from MAG1000: such operation is normal and must not arouse worry.

The manufacturer shall be deemed to be responsible for the performance, reliability, and safety of the appliance only if:

- any additions, modifications and/or repairs are carried out by authorized personnel directly by the manufacturer. Any modification, addition and/or repair performed by unauthorized personnel may result in the loss of safety of the device or its malfunction;
- the electrical system of the environment in which MAG1000 is inserted complies with national laws;
- the appliance is used in strict accordance with the operating instructions contained in this manual.

Patient preparation: positioning of the therapeutic belt

Here below a list of main positions for the therapeutic belt. Wrap the belt around the area to be treated (or position the belt on the area, for example in vertebral column treatment). During this phase **take care to place the green side of the therapeutic belt on the skin.**



Ankle



Hip



Back (lumbar)



Knee



Shoulder



Wrist






Elbow











Cervical

Instructions for use

Follow the instructions for the correct operation of the MAG1000:

- 1) Switch on MAG1000 pressing ON/OFF key .
- 2) Check battery status: if the icon , on the upper side of the display is flashing, proceed to recharge the unit following the instructions (see chapter *Battery charging*).
- 3) Connect the therapeutic belt (or belts) to the plug A (CH1) / B (CH2) on device upper side.
- 4) Chose therapy program running through programs menu, using **PR.** Key
- 5) Set therapy time using **TM.** key: each program has its own set therapy time, which can be modified pressing **TM.** with 5 minutes steps. Therapy time can be increased up to 23 hours and 55 minutes. It's possible to quickly scroll time list pressing **TM.** key
- 6) MAG1000 is now ready for use: the display shows information about the program in use, the working frequency (not adjustable), the adjusted therapy time and field intensity (adjustable during the treatment).
- 7) Press  key: the display will show the remaining therapy time, while it will be possible to modify field intensity during the whole treatment, pressing more times **IN.** key. The relative icon is positioned on the lower right side of the display, with the indication of the three intensities (**1** - low intensity, **2** - medium intensity-two bars and **3** - high intensity).

- 8) The therapy can be suspended pressing the key  : on the bottom right of the display, the flashing indicator will appear . To resume therapy, press again .
- 9) To end the therapy, press key /  : MAG1000 will show again the selected program and adjusted therapy time. To switch off MAG1000, press again key / .
- 10) A sound signal informs of the end of the program, and the display will show the flashing icons 0'00''; to start again a new therapy, press key  and then follow again the indications from step 4).



WARNING: In case no operation is performed for more than 2 minutes, MAG1000 automatically shuts down in order to preserve the battery.

LIST OF STORED PROGRAMS

Pr.	Carrier frequency (MHz)	Squared wave frequency (Hz)	Time (h/min)	Name	Area
P-01	27	8	45min	Arthritis-Arthrosis	Body, arms, legs
P-02	27	8	2h	Rheumatisms	Body, arms, legs
P-03	27	8	4h	Pain- Articular prosthesis	Body, arms, legs
P-04	27	16	45min	Herniated disc	Body
P-05	27	16	2h	Muscular pain	Body, arms, legs
P-06	27	16	4h	Osteoporosis	Body, arms, legs
P-07	27	32	2h	Fractures	Body, arms, legs
P-08	27	32	4h	Sprains	Arms, legs
P-09	27	48	2h	Dislocations	Arms, legs
P-10	27	48	4h	Traumas	Arms, legs
P-11	27	64	2h	Bruises	Arms, legs
P-12	27	64	4h	Myalgia	Arms, legs
P-13	27	80	2h	Tendonitis	Body, arms, legs
P-14	27	80	4h	Hematoma	Body, arms, legs
P-15	27	160	2h	Epicondylitis	Arms
P-16	27	160	4h	Epytrocleitis	Arms

Pr.	Carrier frequency (MHz)	Squared wave frequency (Hz)	Time (h/min)	Name	Area
P-17	27	320	2h	Lumbago	Body
P-18	27	320	4h	Muscular contractures	Body, arms, legs
P-19	27	640	2h	2h Medium application	Body, arms, legs
P-20	27	640	4h	4h Long application	Body, arms, legs

The manufacturer suggests the therapy time as shown on the table and pre-setted on MAG1000. However, the user can adjust the time as he prefers. MAG1000 uses therapy time values, working frequency values and field intensity values coming from scientific and medical literature, as result of well-known sperimentations and clinical evaluations (Barker - Lunt 1983, Bassett – Pawluk – Pilla 1974, Bassett - Valdes – Hernandez 1982).

Maintenance

If used following the instructions given in this user guide, the equipment does not require any particular kind of maintenance.

It is recommended that IACER Srl carries out a functional test every 24 months. The MAG1000 device is not considered to be repairable by any personnel outside the company. Each operation of the kind perpetuated by personnel not authorized by the manufacturer will be considered as tampering the device, freeing the manufacturer from granting warranty and from any danger that the user or the operator may be exposed to.



WARNING: after a long period of inactivity, it may happen that the instrument does not turn on due to battery discharge, not due to actual malfunction; it is appropriate to charge the battery as indicated in the appropriate paragraph before assuming non-existent malfunctions.

CLEANLINESS

To clean the equipment from the dust, use a soft dry cloth. More resistant stains can be removed using a sponge soaked in water and alcohol solution (20% solution). In case of non-prolonged use, clean the device and its accessories as indicated above and store them in the transport bag and store them in the packaging box.

Device not subject to sterilisation.

TRANSPORTATION AND STORAGE

Precaution for the transportation

There is no particular precaution to be taken during transportation of the device, since MAG1000 is a portable device. In any case it is recommended to store MAG1000 and its accessories in the supplied carrying bag after each treatment.

Precaution for the storage

Store the device in a cool, well-ventilated place. Do not store heavy objects on the device.

It is recommended to switch off MAG1000 at the end of each treatment and to remove the cables from the connectors. MAG1000 should be kept in the supplied carrying bag, together with the rest of the equipment supplied and carefully stored on a secure surface. The performances of the equipment are granted if it is stored according to the following conditions:

Outside the carrying bag:

temperature	from +5 to + 40 °C
relative humidity	from 30 to 80%
atmospheric pressure	from 500 to 1060 hPa

Inside the supplied carrying bag:

temperature:	from -10°C to +55°C
maximum relative humidity:	from 10% to 90%
atmospheric pressure:	from 500 to 1060hPa

Troubleshooting


Any type of work on MAG1000 must be carried out exclusively by IACER Srl or by an authorized dealer. In any event, any presumed malfunction of MAG1000 must be verified before sending the device to IACER Srl.



Here below are some typical situations:

- check battery status;
- check the correct connection between MAG1000 and the therapeutic belt;
- check all the operations have been done properly.

If the problem persists contact IACER Srl.

Battery charging

If the battery status is insufficient to complete the working program, the display will show the icon  on the upper right side, near wording PROGRAM.

To proceed with the charging, switch off MAG1000 pressing  and  and connect the battery charger to the plug on the upper side of MAG1000. MAG 1000 is equipped with a software protection that switch off the equipment when the battery charger is connected. Carry out two 5-hour charging cycles (maximum time set for charging) to obtain a full charge of the batteries, as it takes at least 8/10 hours. When the batteries are fully charged, the display displays the full battery charge icon.



WARNING: at the end of the charge wait at least 30 minutes before switching on the device; in order to allow the cooling of the battery pack, overheated during charging and the closure of the integrated safety system that prevents the device from turning on.

Replacing the battery

If, after normal recharging, the battery cannot sustain a full treatment session, recharge again, as it is probably approaching the end of its useful life.

If even after a second recharge the battery still cannot complete a treatment session, follow the steps here below:

- Contact IACER Srl or authorized dealer for original spare part;
- Open the battery compartment on the back side of MAG1000, disconnect the red/black wire from connector and remove the exhausted battery;
- Insert new battery and connect the red/black wire to the plug;
- Close battery compartment.



WARNING: for disposal exhausted battery follow the instructions on chapter *Disposal*.

Do not open or burn battery. Do not short circuit poles. Keep battery away from sparks or naked flames. In the event of internal electrolyte coming into contact with skin or garments, wash immediately with water. In the event of electrolyte coming into contact with eyes, rinse thoroughly and seek medical attention.



WARNING: It is suggested to recharge the device once a month in case of prolonged inactivity. This is for a correct battery maintenance.

Disposal

The MAG1000 magnetotherapy apparatus, compatibly with the operating and safety requirements, has been designed and built to have a minimum negative impact on the environment, following the provisions of the European Directive 2012/19/EU on the disposal of waste electrical and electronic equipment.

The criteria followed are those of minimizing the amount of waste, toxic materials, noise, unwanted radiation and energy consumption.

Careful research on optimizing the efficiency of the machines guarantees a significant reduction in consumption, in harmony with the concepts of energy saving.



This symbol indicates that the product must not be disposed of with another household waste.

The correct disposal of obsolete equipment, accessories and especially batteries, helps to prevent possible negative consequences on human health and the environment.

The user must dispose of the equipment to be scrapped by taking them to the collection center indicated for the subsequent recycling of electrical and electronic equipment.

For more detailed information on disposing of obsolete equipment, please contact the City Council, the waste disposal service or the shop where you purchased the product.

Warranty

IACER Srl guarantees a warranty period from the purchasing date for MAG1000 device, unless information contained in this manual regarding installation, use and maintenance is strictly adhered. The wearing parts (batteries) are not included in the warranty, unless of visible manufacturing defects. The warranty is void in case of tampering of the device and in case of intervention on the same by personnel not authorized by IACER Srl or by the authorized dealer.

The warranty conditions are those described in the following paragraph Warranty conditions. *The warranty is provided by IACER.*

Should you need to return the goods then please pack the device and all the accessories so that it won't be damaged during transportation. In order to be entitled to the warranty assistance, the purchaser must enclose to the device a copy of the purchasing receipt, proving origin and purchasing date.

For more information on the warranty please contact the distributor or vendor, in order to check the norm and standard in force in your Country, or ultimately IACER Srl.

Warranty conditions

- 1) Should assistance be needed, enclose the purchasing receipt when sending the device to IACER Srl.
- 2) The warranty period is valid only on the electronic parts. The warranty will be granted by the shop or directly by IACER Srl.
- 3) The warranty covers only the product damages, which causes its malfunctioning.
- 4) Warranty means that only the manufacturing defect components or material are covered by reparation or free substitution, hand work included.
- 5) Warranty is not applied to damages caused by negligence or use not compliant to the given instructions, by intervention on the device from personnel not authorized, accidental causes or negligence form the purchaser.

- 6) Warranty is not applied in case of damages caused by unsuitable power supplies.
- 7) Warranty does not apply to wearing parts.
- 8) Warranty does not include transportation costs which have to be covered by the purchaser.
- 9) After the warranty period, the warranty is no more applicable. In this case all the assistance interventions will be performed by debiting the costs of the substitution of the parts, the hand work and the transportations costs.
- 10) The court of Venice has exclusive jurisdiction over any dispute.

Assistance

IACER Srl is the sole agent for technical assistance on the equipment. For any technical assistance, please contact:

I.A.C.E.R. S.r.l.

Via Enzo Ferrari 2 • 30037 Scorzè (VE)

Tel. 041.5401356 • Fax 041.5402684

Any technical documentation concerning repairable parts may be provided, but only after company authorization and only after having given adequate instruction to the intervention personnel.

Spare parts

IACER Srl shall make available the original spare parts for the equipment at any time. To request them:

I.A.C.E.R. S.r.l.

Via Enzo Ferrari 2 • 30037 Scorzè (VE)

Tel. 041.5401356 • Fax 041.5402684

For the purpose of maintaining the warranty, the functionality and safety of the product it is recommended to use only original spare parts supplied by IACER Srl (also consult the *Warnings* paragraph).

Interference and electromagnetic compatibility tables

The MAG1000 equipment has been designed and manufactured according to the TECHNICAL STANDARD on ELECTROMAGNETIC COMPATIBILITY legislation EN 60601-1-2 with the aim of providing adequate protection from harmful interference when installed in homes and health establishments.

The apparatus does not generate or receive interference from other equipment. The device should be installed and put into service in accordance with the information contained in the accompanying documents.

Wireless communication devices such as home wireless devices (modem/router), mobile phones, cordless phones and their charging bases, walkie-talkies can interfere with the device and should be kept at least at a distance d from the device. The distance d is calculated by the manufacturer in the column 800MHz to 2.5GHz of the ELECTROMAGNETIC IMMUNITY TO RF table in the following paragraph.

For more details consult the compatibility tables in Italian/English at the end of the manual.

MAG1000. All rights reserved. MAG1000 and **I-TECH MEDICAL DIVISION** logos are owned by IACER and are registered.

Edition: MNPG552-00 of the April 30th, 2024

TABELLE DI COMPATIBILITÀ Elettromagnetica – ELECTROMAGNETIC COMPATIBILITY TABLES

Dichiarazione – EMISSIONI Elettromagnetiche <i>Declaration – ELECTROMAGNETIC EMISSIONS</i>		
<p>Il prodotto MAG1000 è previsto per funzionare nell'ambiente elettromagnetico sotto specificato. Il cliente o l'utilizzatore di tale dispositivo deve garantire che esso venga usato in tale ambiente.</p> <p><i>The MAG1000 device is expected to operate in the electromagnetic environment below specified. The customer or user of the MAG1000 device must ensure that it is used in such an environment.</i></p>		
Prova di emissione <i>Emission test</i>	Conformità <i>Compliance</i>	Ambiente elettromagnetico – Guida <i>Electromagnetic environment – guidance</i>
Emissioni RF <i>RF emissions</i> CISPR 11	Gruppo 1 <i>Group 1</i>	Il prodotto MAG1000 utilizza energia RF solo per il suo funzionamento interno. Perciò le sue emissioni RF sono molto basse e verosimilmente non causano nessuna interferenza negli apparecchi elettronici vicini <i>MAG1000 device uses RF energy only for its internal function. Therefore, its RF emissions are very low and are unlikely to cause any interference in nearby electronic equipment</i>
Emissioni RF <i>RF emissions</i> CISPR 11	Classe B <i>Class B</i>	Il prodotto MAG1000 è adatto per l'uso in tutti gli edifici diversi da quelli domestici e da quelli collegati direttamente ad una rete di alimentazione a bassa tensione che alimenta gli edifici domestici, e quelli direttamente collegati alla rete di alimentazione pubblica in bassa tensione che alimenta edifici per usi domestici. <i>MAG1000 is suitable for use in all establishments, including domestic establishments and those directly connected to the public low-voltage power supply network that supplies buildings used for domestic purposes.</i>
Emissioni armoniche <i>Harmonic emissions</i> IEC 61000-3-2	Classe A <i>Class A</i>	
Emissioni di fluttuazioni di tensione/flicker <i>Voltage fluctuations/flicker emissions</i> IEC 61000-3-3	Conforme <i>Compliant</i>	

Dichiarazione – IMMUNITÀ ELETTROMAGNETICA <i>Declaration – ELECTROMAGNETIC IMMUNITY</i>			
<p>Il prodotto MAG1000 è previsto per funzionare nell'ambiente elettromagnetico sotto specificato. Il cliente o l'utilizzatore di tale dispositivo deve garantire che venga usato in tale ambiente.</p> <p><i>MAG1000 is intended for use in the electromagnetic environment specified below. The user or operator of MAG1000 should assure that is used in such environment.</i></p>			
Prova di immunità <i>Immunity test</i>	Livello di prova <i>Test level</i> IEC 60601	Livello di conformità <i>Compliance level</i>	Ambiente elettromagnetico – Guida <i>Electromagnetic environment – guidance</i>
Scarica elettrostatica (ESD) <i>Electrostatic discharge (ESD)</i> IEC 61000-4-2	$\pm 8\text{kV}$ a contatto / <i>at contact</i> $\pm 2\text{kV}$, $\pm 4\text{kV}$, $\pm 8\text{kV}$, $\pm 15\text{kV}$ in aria / <i>in air</i>	$\pm 8\text{kV}$ a contatto / <i>at contact</i> $\pm 2\text{kV}$, $\pm 4\text{kV}$, $\pm 8\text{kV}$, $\pm 15\text{kV}$ in aria / <i>in air</i>	I pavimenti devono essere in legno, calcestruzzo o in ceramica. Se i pavimenti sono ricoperti di materiale sintetico, l'umidità relativa dovrebbe essere almeno 30%. <i>Floors should be wood, concrete or ceramic tie. If floor is covered with synthetic material, the relative humidity should be at least 30%.</i>
Transitori/treni elettrici veloci <i>Electrical transient/burst</i> IEC 61000-4-4	$\pm 2\text{kV}$ per le linee di alimentazione di potenza <i>for power supply lines</i> $\pm 1\text{kV}$ per le linee di input/output <i>for power supply lines</i>	$\pm 2\text{kV}$ per le linee di alimentazione di potenza <i>for power supply lines</i> $\pm 1\text{kV}$ per le linee di input/output <i>for power supply lines</i>	La qualità della tensione di rete dovrebbe essere quella di un tipico ambiente commerciale o ospedaliero. <i>Mains power quality should be that of a typical commercial or hospital environment.</i>
Sovratensioni <i>Surge</i> IEC 61000-4-5	$\pm 0.5\text{kV}$, $\pm 1\text{kV}$ linea - linea / <i>line(s) to lines</i> $\pm 0.5\text{kV}$, $\pm 1\text{kV}$,	$\pm 0.5\text{kV}$, $\pm 1\text{kV}$ linea - linea / <i>line(s) to lines</i> $\pm 0.5\text{kV}$, $\pm 1\text{kV}$,	La qualità della tensione di rete dovrebbe essere quella di un tipico ambiente

Dichiarazione – IMMUNITÀ ELETTROMAGNETICA

Declaration – ELECTROMAGNETIC IMMUNITY

Il prodotto MAG1000 è previsto per funzionare nell'ambiente elettromagnetico sotto specificato. Il cliente o l'utilizzatore di tale dispositivo deve garantire che venga usato in tale ambiente.

MAG1000 is intended for use in the electromagnetic environment specified below. The user or operator of MAG1000 should assure that it is used in such environment.

Prova di immunità <i>Immunity test</i>	Livello di prova <i>Test level</i> IEC 60601	Livello di conformità <i>Compliance level</i>	Ambiente elettromagnetico – Guida <i>Electromagnetic environment – guidance</i>
	±2kV linea - terra / <i>line(s) to earth</i>	±2kV linea - terra / <i>line(s) to earth</i>	commerciale o ospedaliero. <i>Mains power quality should be that of a typical commercial or hospital environment.</i>
Buchi di tensione, brevi interruzioni e variazioni di tensione sulle linee di ingresso dell'alimentazione <i>Voltage dips, short interruptions and voltage variations on power supply input lines</i> IEC 61000-4-11	0% U _T ; 0.5 cicli a / <i>cycle at 0°, 45°, 90°, 135°, 180°, 225° e/and 315°</i> 0% U _T ; 1 ciclo e/ / <i>cycle and 70% U_T; 25/30 cicli/ cycles</i> Singola fase: a 0° / <i>Single phase: at 0°</i> 0% U _T ; 250/300 cicli / <i>cycles</i>	0% U _T ; 0.5 cicli a / <i>cycle at 0°, 45°, 90°, 135°, 180°, 225° e/and 315°</i> 0% U _T ; 1 ciclo e/ / <i>cycle and 70% U_T; 25/30 cicli/ cycles</i> Singola fase: a 0° / <i>Single phase: at 0°</i> 0% U _T ; 250/300 cicli / <i>cycles</i>	La qualità della tensione di rete dovrebbe essere quella di un tipico ambiente commerciale o ospedaliero. Se l'utilizzatore del prodotto MAG1000 richiede un funzionamento continuo anche durante l'interruzione della tensione di rete, si raccomanda di alimentare l'apparecchio MAG1000 con un gruppo di continuità (UPS) o con batterie. <i>Mains power quality should be at least that one of a typical commercial or hospital environment.</i>

Dichiarazione – IMMUNITÀ ELETTROMAGNETICA Declaration – ELECTROMAGNETIC IMMUNITY			
<p>Il prodotto MAG1000 è previsto per funzionare nell'ambiente elettromagnetico sotto specificato. Il cliente o l'utilizzatore di tale dispositivo deve garantire che venga usato in tale ambiente.</p> <p><i>MAG1000 is intended for use in the electromagnetic environment specified below. The user or operator of MAG1000 should assure that is used in such environment.</i></p>			
Prova di immunità Immunity test	Livello di prova Test level IEC 60601	Livello di conformità Compliance level	Ambiente elettromagnetico – Guida Electromagnetic environment – guidance
			<p><i>If the user of the MAG1000 requires continued operating during power mains interruptions, it is recommended that MAG1000 be powered from an uninterruptible power supply (UPS) or a battery</i></p>
<p>Campo magnetico a frequenza di rete (50/60Hz) Power frequency magnetic field (50/60Hz) IEC 61000-4-8</p>	<p>30 A/m</p>	<p>30 A/m</p>	<p>I campi magnetici a frequenza di rete dovrebbero avere livelli caratteristici di una località tipica in ambiente commerciale o ospedaliero. Power frequency magnetic fields should be at levels characteristic of a typical location in a typical commercial or hospital environment.</p>
<p>Nota: U_T è la tensione di rete in c.a. prima dell'applicazione del livello di prova. Note: U_T is the AC mains voltage prior to the application of the Test level.</p>			

Dichiarazione – IMMUNITÀ ELETTROMAGNETICA <i>Declaration – ELECTROMAGNETIC IMMUNITY</i>			
<p>Il prodotto MAG1000 è previsto per funzionare nell'ambiente elettromagnetico sotto specificato. Il cliente o l'utilizzatore di tale dispositivo deve garantire che venga usato in tale ambiente.</p> <p><i>MAG1000 is intended for use in the electromagnetic environment specified below. The user or operator of MAG1000 should assure that is used in such environment.</i></p>			
Prova di immunità <i>Immunity test</i>	Livello di prova <i>Test level</i> IEC 60601	Livello di conformità <i>Compliance level</i>	Ambiente elettromagnetico – Guida <i>Electromagnetic environment – guidance</i>
<p>Gli apparecchi di comunicazione a RF portatili e mobili non dovrebbero essere usati vicino a nessuna parte dell'apparecchio MAG1000, compresi i cavi, eccetto quando sono rispettate le distanze di separazione raccomandate, calcolate dall'equazione applicabile alla frequenza del trasmettitore.</p> <p><i>Portable and mobile RF communications equipment should not be used near any part of the MAG1000 device, including cables, except where recommended separation distances are observed, calculated from the equation applicable to frequency of the transmitter.</i></p>			
Distanza di separazione raccomandata- <i>Recommended separation distance</i>			
RF condotta <i>Conducted RF</i> IEC 61000-4-6	3V da 0.15MHz a 80 MHz 3V <i>from</i> 0.15MHz <i>to</i> 80MHz 6V da 0.15MHz a 80MHz per banda ISM 6V <i>in ISM and amateur radio bands from</i> 0.15MHz <i>to</i> 80MHz	3V da 0.15MHz a 80 MHz 3V <i>from</i> 0.15MHz <i>to</i> 80MHz 6V da 0.15MHz a 80MHz per banda ISM 6V <i>in ISM and amateur radio bands from</i> 0.15MHz <i>to</i> 80MHz	Distanze di separazione raccomandate $d = 1,2\sqrt{P}$ da 150kHz a 80MHz $d = 1,2\sqrt{P}$ da 80MHz a 800MHz $d = 2,3\sqrt{P}$ da 800MHz a 2,5GHz <i>Recommended separation distance:</i> $d = 1,2 \cdot \sqrt{P}$ 150kHz to 80MHz $d = 1,2 \cdot \sqrt{P}$ 80 MHz to 800 MHz $d = 2,3 \cdot \sqrt{P}$ 800 MHz to 2,5 GHz
RF irradiata <i>Irradiated RF</i> IEC 61000-4-3	10V/m da 80MHz a 2.7GHz / <i>from</i> 80MHz <i>to</i> 2.7GHz	10 V/m	

Dichiarazione – IMMUNITÀ ELETTROMAGNETICA

Declaration – ELECTROMAGNETIC IMMUNITY

ove P è la potenza massima nominale d'uscita del trasmettitore in Watt (W) secondo il costruttore del trasmettitore e d è la distanza di separazione raccomandata in metri (m). Le intensità di campo dei trasmettitori a RF fissi, come determinato da un'indagine elettromagnetica^a del sito potrebbe essere minore del livello di conformità in ciascun intervallo di frequenza^b

Si può verificare interferenza in prossimità di apparecchi contrassegnati dal seguente simbolo:



where (P) is the maximum output power rating of the transmitter in Watts (W) according to the transmitter manufacturer and (d) is the recommended separation distance in meters (m).

Field strengths from fixed RF transmitters, as determined by an electromagnetic site survey^a, should be less than the compliance level in each frequency range^b.

Interference may occur in the vicinity of equipment marked with the following symbol:

Note:

- (1) A 80 MHz e 800 MHz; si applica l'intervallo di frequenza più alto / At 80 MHz and 800 MHz the separation distance for the higher frequency range applies.
 - (2) Queste linee guida potrebbero non applicarsi in tutte le situazioni. La propagazione elettromagnetica è influenzata dall'assorbimento e dalla riflessione di strutture, oggetti e persone / These guidelines may not apply in all situations. Electromagnetic propagation is affected by absorption and reflection from structures, objects and people.
- a) Le intensità di campo per trasmettitori fissi come le stazioni base per radiotelefoni (cellulari e cordless) e radiomobili terrestri, apparecchi di radioamatori, trasmettitori radio in AM e FM e trasmettitori TV non possono essere previste teoricamente e con precisione. Per valutare un ambiente elettromagnetico causato da trasmettitori RF fissi, si dovrebbe considerare un'indagine elettromagnetica del sito. Se l'intensità di campo misurata nel luogo in cui si usa un MAG2000, supera il livello di conformità applicabile di cui sopra, si dovrebbe porre sotto osservazione il funzionamento normale del MAG2000. Se si notano prestazioni anormali, possono essere necessarie misure aggiuntive come un diverso orientamento o posizione del MAG1000 / Field strengths from fixed transmitters, such as base stations for radio (cellular/cordless) telephones and land mobile radios, amateur radio, AM and FM radio broadcast and TV broadcast cannot be predicted theoretically with accuracy. To assess the electromagnetic environment due to fixed RF transmitters, an electromagnetic site survey should be considered. If the measured field strength in the location in which the MAG1000 is used exceeds the applicable RF compliance level above, the MAG1000 should be observed to verify normal operation. If abnormal performance is observed, additional measures may be necessary, such as re-orienting or relocating the MAG2000.
- b) L'intensità di campo nell'intervallo di frequenza da 150 kHz a 80 MHz dovrebbe essere minore di 3V/m. / Over the frequency range 0.15MHz to 80MHz, field strengths should be less than 3 V/m.

Distanze di separazione raccomandate tra apparecchi di radiocomunicazione portatili e mobili per il dispositivo MAG1000

Recommended separation distances between portable and mobile RF communications equipment for MAG1000

Il prodotto MAG1000 è previsto per funzionare in un ambiente elettromagnetico in cui sono sotto controllo i disturbi irradiati RF. Il cliente o l'operatore dell'apparecchio possono contribuire a prevenire interferenze elettromagnetiche assicurando una distanza minima fra gli apparecchi di comunicazione mobili e portatili a RF (trasmettitori) e l'apparecchio, come sotto raccomandato, in relazione alla potenza di uscita degli apparecchi di radiocomunicazione.

MAG1000 is intended for the use in an electromagnetic environment in which radiated RF disturbances are controlled. The user or the operator of MAG1000 can help prevent electromagnetic interferences by maintaining a minimum distance between portable and mobile RF communications equipment (transmitters) and MAG1000 as recommended below, according to the maximum output power of the communication equipment.

Potenza di uscita massima del trasmettitore specificata (W) <i>Rated maximum power of the transmitter (W)</i>	Distanza di separazione alla frequenza del trasmettitore (m) <i>Separation distance according to the frequency of transmitter (m)</i>		
	<i>da 150kHz a 80MHz from 150kHz to 80 MHz $d = 1,2\sqrt{P}$</i>	<i>da 80MHz a 800MHz 80MHz to 800MHz $d = 1,2\sqrt{P}$</i>	<i>da 800MHz a 2,5GHz 800MHz to 2,5GHz $d = 2,3\sqrt{P}$</i>
0,01	0,12	0,12	0,23
0,1	0,38	0,38	0,73
1	1,2	1,2	2,3
10	3,8	3,8	7,3
100	12	12	23

Per i trasmettitori con potenza nominale massima di uscita sopra non riportata, la distanza di separazione raccomandata d in metri (m) può essere calcolata usando l'equazione applicabile alla frequenza del trasmettitore, dove P è la potenza massima nominale d'uscita del trasmettitore in watt (W) secondo il fabbricante del trasmettitore.

For transmitters rated at a maximum output power not listed above, the recommended separation distance d in meters (m) can be estimated using the equation applicable to the frequency of the transmitter, where P is the maximum output power rating of the transmitter in Watts (W) according to the transmitter manufacturer.

Nota / Note

- (1) A 80 MHz e 800 MHz, si applica l'intervallo della frequenza più alto / At 80 MHz and 800 MHz the separation distance for the higher frequency range applies.
- (2) Queste linee guida potrebbero non applicarsi in tutte le situazioni. La propagazione elettromagnetica è influenzata dall'assorbimento e dalla riflessione di strutture, oggetti e persone / These guidelines may not apply in all situations. Electromagnetic propagation is affected by absorption and reflection from structures, objects and people.

I-TECH
MEDICAL DIVISION



I.A.C.E.R. S.r.l.

Via Enzo Ferrari 2 - 30037, Scorzè (VE) – Italy

Tel.: (+39) 041 540 13 56 | Email: iacer@iacer.it

www.itechmedicaldivision.com

Share Capital: € 1.000.000 fully paid-up

Tax Code / VAT Number: IT 00185480274

Certified email: iacer@pec.it | SDI: SUBM70N

Edition: MNPG550-00 of the April 30th, 2024